

Motor Driven Bell - 24 Vdc

MB Series

Features

- Mounts to standard 4" square electrical box
- Wire lead design
- High quality micromotor
- Loud resonant tones
- Low current drawn
- 6" and 10" (150 and 250 mm) sizes
- "Fire Red" Finish

Description

EST MB Series Motor Driven Bells are specially designed for Fire Alarm applications. The gongs are made from select alloy chosen to give the loud, resonant tones necessary in fire alarm and life safety systems. Two sizes of gongs are available to help overcome different ambient noise levels.

EST MB bells are the "under-dome" type and use heavy duty mechanisms. The bell's base and gong are finished with a durable "Fire Red" baking enamel.

All MB bells mount on any standard North-American 4 inch square electrical box.

Field wiring connections are made to colour-coded leads.



Ordering Information

Catalogue No.	Description	Ship Wt.(kg)
MB6-24	6" (150mm) Fire Alarm Bell - Red Finish	1.0
MB10-24	10" (250mm) Fire Alarm Bell - Red Finish	1.9
Accessories		
512-1	Wallbox - for flush mounting MB6-24 into wall	2.5
512-10	Ceiling Box - for flush mounting MB6-24 into ceiling	3.5
512-2	Grille c/w Prime Paint Coat - for 512 series backbox	1.0
512-3	Grille c/w Brushed Stainless Steel Finish - for 512 series backbox	1.0
513-1	Wallbox - for flush mounting MB10-24 into wall	4.5
513-10	Ceiling Box - for flush mounting MB10-24 into ceiling	6.0
513-2	Grille c/w Prime Paint Coat - for 513 series backbox	1.5
513-3	Grille c/w Brushed Stainless Steel Finish - for 513 series backbox	1.5
MBFP-1	"Flush Mounting Plate -Red Finish. For 4" Square Outlet Box (by others)"	.5
MBFP-2	Flush Mounting Plate -Red Finish. Multiple Backbox Mounting	.5
BBX-4	Weather Proof Wall Box	1.5
403-*A-R	Series Bell Strobe Plate See Lit sheet 85001-0509	.9