

240Vac FIRE MARKET



WR2001/SR



WR7/2001



WR4001

Manual Break Glass Fire Alarm Call Points to suit all environments. Providing single pole changeover contacts, all models are suitable for mains voltage systems.



Device Type	Manual Break Glass Call Point		
Installation	INDOOR	RAINPROOF	WATERPROOF
Ingress Protection	IP24D	IP55	IP67
Circuit Configuration	Single Pole Changeover Contacts		
Contact Rating	3A 240Vac 3A 30Vdc	3A 240Vac 3A 30Vdc	5A 240Vac 5A 30Vdc
Approvals	BS5839:Part 2 Certified by Loss Prevention Certification Board		
Operating Temperature Range	-30°C to +70°C		
	Order Codes		
Surface	MUS002W	MUS119W	MUS020W
Flush	MUS001W	N/A	N/A

E. & O.E.

Document Ref.
LIT:171
May 2001